



A five channel amplifier with power to drive any home theatre system to realistic levels.

**The COPLAND CVA535** retains its stylish exterior with emphasis on build quality, efficient air flow and temperature control.

A single chassis employs five independent amplifier modules, each with its own rectifiers, filtering and regulation etc.

By keeping the entire channel on a single circuit board, the length of the pcb tracks are kept to an absolute minimum for accurate dynamics and spatial image.

The CVA535 has a built-in soft start circuit for prolonged reliability with the added safeguard of DC and thermal protection for extra assurance.

All channels accepts single ended as well as balanced inputs and the standby switch can be controlled from either the COPLAND CVA306 pre-amplifier or the system remote control.

Dealer:

### Specifications

|                        |   |
|------------------------|---|
| Output power:          | 5 x 125 W @ 8 ohms  |
| T.H.D.                 | Less than 0.05% at all levels.                                |
| Frequency response:    | 10Hz-30KHz -0,2dB   |
| Input sensitivity:     | 1,4 V for rated power   |
| Input impedance:       | 100K ohms ( RCA )<br>12K ohms (Balanced)                      |
| Signal / Noise:        | Better than 103 dB IHF-A curve.                               |
| Power consumption:     | 1300 W  |
| Nominal mains voltage: | 115V or 230V<br>Factory set for the destination country only. |
| Mains voltage range:   | +/- 12%   |
| Shipping weight:       | 30 Kg   |
| Dimensions:            | 430 (W) 168 (H) 420 (D)                                       |