



# Dream Vision

## Odyssee 30

TFT - PAL TUNER - AUDIO BUILT-IN - FULL GLASS

<b>Display panel</b>	<b>Screen size</b>	30" (75 cm) diagonal	
	<b>Aspect Ratio</b>	15:9	
	<b>Resolution</b>	1280 (H) x 768 (V) pixels	
	<b>Brightness</b>	500 cd/m <sup>2</sup>	
	<b>Contrast ratio</b>	500:1	
	<b>View angle</b>	H:170°, V:170°	
	<b>Colors</b>	16.77 Mil	
<b>Connections</b>	<b>Video</b>	Video [CVBS] S-Video [Y/C] SCART [CVBS, RGB] Component [Y,Pb,Pr]	
	<b>PC</b>	Analog RGB [PC] Digital RGB [DVI-D]	
	<b>Tuner</b>	Antenna [75 Ohm - VHF/UHF]	
	<b>Audio</b>	Video stereo input S-Video stereo input Component stereo input PC stereo input Line stereo output Power stereo output, speakers [cinch]	
	<b>Control</b>	RS232	
	<b>Video</b>	PAL (BGH/D/I, M, N, 60), NTSC (M, 4.43), SECAM	
	<b>PC</b>	VGA ~ SXGA (1280x1024) NATIVE (1280x768)	
	<b>DTV</b>	YPbPr: 480i, RGB-PC: 480i/p, 720p, 1080i	
	<b>Tuner</b>	Standard: PAL BG//DK, SECAM L/L' Tuning system: Electronic with PLL Teletext: BESIC1.5/TOP/FAST	
	<b>Audio</b>	Power audio output: 2 x 7W	
<b>Speakers</b>	Built-in stereo speakers		
<b>Controls</b>	<b>Video</b>	Brightness, Contrast, Color, Sharpness Colour temperature (3 selections) Size (fill screen, fit to aspect, letter box, TV mode) PIP (on PC only) Still	
	<b>TV</b>	Auto scan Search/fine tune Auto station name Edit program	
	<b>Audio</b>	Volume, Balance, Treble, Bass Equalizer Internal/External speaker selection Stereo/mono/dual sound/NICAM AutomaticVolumeControl	
	<b>Others</b>	Sleep mode	
	<b>OSD Language</b>	D, E, F, GB, I	
	<b>Physical</b>	<b>Dimensions</b>	753 (W) x 480 (H) x 95 (D) (without base)
		<b>Weight</b>	24 Kg (without base)
		<b>Mains voltage</b>	115/230 VAC ± 15%, 50/60 Hz
		<b>Power consumption</b>	150 W
	<b>Accessories</b>		Power cable
			Remote control with batteries
			User manual

Those specifications may be modified once this product is mass produced.